MASTER LEDtube HF InstantFit T8 – 600 mm

Ballast Compatibility

KEY

	Ballast is compatible
*	Ballast is compatible, light output may differ >10% compared to specifications
	Ballast is not compatible

This document is for information purposes and must be treated as recommendation. Philips attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions

HF Works with High Frequency ballast (HF)

InstantFit™

	Ballast type	10nc / Ref. no.	Lamps on ballast	MASTER LEDtube HF, Instant Fit 600mm HF 1050lm Model number / EOC code: 9290013931 / 871869674353900 9290013932 / 871869674355300 9290013933 /871869674367600
				AC (50Hz) on HF Ballast Compatible
PHILIPS	HF-P 118 TLD III IDC	9137130312	1	
	HF-P 218 TLD III IDC	9137130313	2	
	HF-S 118 TLD II	9137130320	1	
	HF-S 218 TL-D II 220-240V 50/60Hz	9137130323	2	
	HF-S 3/4x18 TLD II	9137130326	3	
	HF-S 3/4x18 TLD II	9137130326	4	
	HF-Matchbox 1x18 Blue	9137004180 / 9137004179	1	
	HF-Matchbox 1x18 RED		1	
	HF-P 3/4x18 TLD III IDC	9137130314	3	
	HF-P 3/4x18 TLD III IDC	9137130314	4	
	HF-E 136 TL-D II 220-240V 50/60Hz (HF-E 218 TLD)	9137130390	2	
	HF-E 418 TL-D II 220-240V 50/60Hz-parl	9137130412	4	
	HF-P 118 TLD 220-240	9137001709	1	
	HF-P 118/136 TL-D III	9137130315	1	
	HF-S 118/136 TL-D II	9137130321	1	
	HF-P 218/236 TL-D III	9137130316	2	
	HF-S 218/236 TL-D II	9137130324	2	
OSRAM	QTP8 1x18		1	
	QTP8 2x18		2	
	QT-FIT8 1x18		1	
	QT-FIT8 2x18		2	
	QT Fit 5/8 1x18-39		1	
	QTP-OPTIMAL 118-40		1	
	QTP-OPTIMAL 218-40		2	
	QT Fit 5/8 2x18-39		2	
	QT-FIT8 3/4X18		3	
	QT-FIT8 3/4X18		4	
HELVAR	EL1x18ngn		1	
	EL2x18ngn		2	
	EL 3/4x18ngn		4	*
	EL 3/4x18ngn		3	
	EL1x18s		1	
	EL 4x18ngn		4	
TRIDONIC ATCO	PC 118 PRO lp	22185213	1	
	PC 218 PRO lp	22185216	2	
	PC 1X18-24W BASIC	22176000	1	
	PC 1x18 T8 TOP sl	22185222	1	
	PC 3/4X18 TOP lp	22185219 / 22185228	3	
	PC 3/4X18 TOP lp	22185219 / 22185228	4	
	PC 1/14-35/24/39 T5 PRO-M lp	22176182	1	
	PC 2/14-35/24/39 T5 PRO-M lp	22176185	2	
	PC 1x18 T8 TEC	87500113	1	
	PC 2x18 T8 TEC	87500114	2	
	PC 2x36 T8 TEC (4x18 T8 TEC)	87500116	4	
VOSSLOH-SCHWABE	ELXc 136.200	188314	1	
	ELXc 236.208		2	
	ELXc 424.379	188116	3	
	ELXc 424.379	188116	4	
	ELXc 418.204	188318	3	
	ELXc 418.204	188318	4	
	ELXc 136.207		1	
BAG-HUECO	BCS18.1FX-11/220-240	1007 7588	1	
	BCS18.2FX-11/220-240	1007 7589	2	
	BCS18.3-4LR-01/220-240 3lamp	1005 0999	3	
	BCS18.3-4LR-01/220-240 4lamp	1005 0999	4	
Others	Direct mains			
	Electro Magnetic Ballast			

General note Philips Master LEDtube HF InstantFit T8

General notes: Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.
Please note that Philips LEDtubes InstantFit T8 are only tested with HF ballast on AC operation. The performance of Philips LEDtubes InstantFit T8 on HF ballasts with DC operation is not tested and is therefore not guaranteed. Philips LED tube InstantFit range is designed to work on HF ballasts only. For EM ballasts or direct mains connection, please contact a Philips sales representative for more information on our EM/Mains compatible range. This document is for information purposes only and must be treated as recommendation. Philips will not accept claims for any damage caused by not implementing the recommendations in this document. Philips does not accept any responsibility, warranty or liability when using Philips LEDtubes with ballasts not mentioned in this list, or when using successor models of the tested ballasts. Although Philips aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips LEDtube. Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on www.philips.com/ledtube

Dimming a LEDtube: Philips 600mm MASTER LEDtubes InstantFit T8 are not developed for dimming therefore the performance cannot be guaranteed in a dimming application. In case of usage of a non-dimmable product in a dimmable application, warranty does not apply.