

SubstiTUBE® T8 Value HF

1.2m Ballast compatibility (1200mm)

| | |
|--|--|
| | compatible |
| | * compatible but may differ >10% of luminous flux of specification |
| | not compatible |

| Brand | Model | EAN / Ref.no | Lamps on ballast | ST8V 17W HF |
|------------------|---------------------|---------------|------------------|--|
| | | | | Product EAN10 No. 4052899955950 4052899955967 4052899955974 |
| OSRAM | QT Fit 5/8 1x18-39 | 4008321873927 | 1 | |
| | QT Fit 5/8 2x18-39 | 4008321873903 | 2 | |
| | QT FIT8 1x36 | 4008321294203 | 1 | |
| | QT FIT8 2x36 | 4008321294265 | 2 | |
| | QTP8 1x36 | 4008321131621 | 1 | |
| | QTP8 2x36 | 4008321131645 | 2 | |
| | QTP-OPTIMAL 1x18-40 | 4008321873743 | 1 | |
| | QTP-OPTIMAL 2x18-40 | 4008321873767 | 2 | |
| Philips | HF-B 136 TL-D EII | 8711500931542 | 1 | |
| | HF-B 236 TL-D | 91370 01124 | 2 | |
| | HF-B 236 TL-D EII | 8711500931580 | 2 | |
| | HF-P 136 TL-D III | 8711500999641 | 1 | |
| | HF-P 236 TL-D EII | 8711500912022 | 2 | |
| | HF-P 236 TL-D III | 8727900911664 | 2 | |
| | HF-P 336 TL-D III | 8711500999689 | 3 | |
| | HF-S 236 TL-D II | 8718291796978 | 2 | |
| HF-S 336 TL-D II | 8711500999092 | 3 | | |
| Helvar | EL1x36/40/18s | | 1 | |
| | EL1x36ngn | | 1 | |
| | EL2x36/40s | | 2 | |
| | EL2x36HF | | 2 | |
| Tridonic | PC 1/30 T8 PRO | 22176077 | 1 | |
| | PC 1/36 T8 PRO sc | 22083162 | 1 | |
| | PC 1x36 T8 PRO Ip | 22185214 | 1 | |
| | PC 1x36 T8 TOP sl | 22185223 | 1 | |
| | PC 2x36 T8 PRO sl | 22185217 | 2 | |
| | PC 2x36 T8 TOP sl | 22185226 | 2 | |
| Vossloh | ELXc 136.200 | 188314 | 1 | |
| | ELXc 136.207 | 188708 | 1 | |
| | ELXc 136.216 | 188912 | 1 | |
| | ELXc 236.208 | 188705 | 2 | |
| | ELXc 236.217 | 188913 | 2 | |
| | ELXc 336.214 | 188595 | 3 | |
| b,a,g, | BCS36.1FX-11 | 10077590 | 1 | |
| | BCS36.2FX-11 | 10077591 | 2 | |
| Trilux | D58.1-23021 E 136W | 4046189001816 | 1 | |